

FIXED POWER SUPPLY 6 V OR 12 V, DC OR AC 5A

Reference : AM061205



- Complete: Continuous and alternative voltages available simultaneously
- Practical: Continuous and alternative operation indicator
- Protected: continuous output protected by current limiting, alternative outputs protected by automatic reset thermal circuit breakers.

All outlets are floating and on \varnothing 4 mm safety sockets
The maximum power of these power supplies is 120 W.
Alternate and continuous outputs can be used together on circuits without a common reference.

| | |
|--------------------------|--|
| Reference | AM061205 |
| Number of outputs | 2 |
| DC voltage | 6 or 12 V |
| AC voltage | 6 or 12 V |
| Max intensity | 5.0 A |
| Precision | 1% |
| Ondulation | - |
| Display | No |
| Protection | Continuous output protected by current limiting, |

| | |
|-------------------|---|
| | alternative outputs protected by automatic reset thermal circuit breakers |
| Dimensions | 120 x 120 x 120 mm |
| Mass | 2.15 kg |
| Warranty | 2 years |